

< Specifications. >

Version:A0

(PIC) Model No.				
	BR-FL70W-07(ID:TA)	BR-FL80W-07(ID:TA)	BR-FL100W-07(ID:TA)	BR-FL120W-07(ID:TA)

Photoelectric Spec

Item	Power	Input Voltage	Input Frequency	leds	Power Factor	LuminousFlux	Beam Angle	Weight
BR-FL70W-07(ID:TA)	70W	AC100-240V	50/60HZ	COB	>0.9	5600 Lm	120°	4.1 kg
BR-FL80W-07(ID:TA)	80W	AC100-240V	50/60HZ	COB	>0.9	6400 Lm	120°	4.1 kg
BR-FL100W-07(ID:TA)	100W	AC100-240V	50/60HZ	COB	>0.9	8000 Lm	120°	5.6 kg
BR-FL120W-07(ID:TA)	120W	AC100-240V	50/60HZ	COB	>0.9	9600 Lm	120°	5.6 kg

Light Source Spec

LED Type	Epistar
Color Accuracy(CRI)	CRI>70
Color	WW(3000-3500K) NW (4000-4500K) CW(5000-6500K)





Environment Spec.









Operational Temperature Range	-20~50 °C
Preservation Temperature Range	-40~60 °C
Operational Humidity Range	95% Rh or below(@-20°C~50°C)
Installation Area	Outdoor:IP65(Roadway, Pathway, Sidewalk,etc)
Lifespan	3 Years

Certification standard






Dimension Diagram

BR-FL70W-07(ID:TA)	BR-FL80W-07(ID:TA)
	
BR-FL100W-07(ID:TA)	BR-FL120W-07(ID:TA)
	

BR-FL70W-07(ID:TA)	Radiation  AVERAGE BEAM ANGLE (50%) :112.9 DEG	Lux Diagram  Height Eavg,Emax Angle:109.67deg Diameter Note:The Curves indicate the illuminated area and the average illumination when the luminaire is at different distance.
BR-FL80W-07(ID:TA)	Radiation  AVERAGE BEAM ANGLE (50%) :113.1 DEG	Lux Diagram  Height Eavg,Emax Angle:110.00deg Diameter Note:The Curves indicate the illuminated area and the average illumination when the luminaire is at different distance.
BR-FL100W-07(ID:TA)	Radiation  AVERAGE BEAM ANGLE (50%) :113.1 DEG	Lux Diagram  Height Eavg,Emax Angle:111.09deg Diameter Note:The Curves indicate the illuminated area and the average illumination when the luminaire is at different distance.
BR-FL120W-07(ID:TA)	Radiation  AVERAGE BEAM ANGLE (50%) :115.0 DEG	Lux Diagram  Height Eavg,Emax Angle:112.36deg Diameter Note:The Curves indicate the illuminated area and the average illumination when the luminaire is at different distance.

Installation and use

1.First,adjust the angle you need,finally fasten the floodlights with screws	2.Install the LED Floodlight onto the wall or ground,punch hole on the wall orground,prepare the expansion screw,and then fasten the floodlight
	
3.Connect the power wire from the Main lineeto the power wire of the lamp,and then make treatment for water reistance. Pls note that the Brown color wire is Live wire,Blue wire is Null line,the yellow and green wire is Earth line.	4.Turn on the power supply to ensuer the light is working,Installed.
	

Attention

1.Please turn off the power supply befor installation or changing assembly parts.

2.The input voltage and the lamp should be adapted. After connecting the power line, please make sure the wiring section is insulated.

3.Non-professionals, must not install or dismantle the lamps.

4.All the floodlights during installation and in use should not be put with glass cover vertically upside.

Packing Spec


Item	Box			Carton		
	Measurement (mm)	Gross weight	Pcs/box	Measurement(mm)	Gross weight	Pcs/carton
BR-FL70W-07(ID:TA)	L335*W290*H135	4.25 kg	1	L 610*W355*H300	18.4 kg	4
BR-FL80W-07(ID:TA)	L335*W290*H135	4.25 kg	1	L 610*W355*H300	18.4 kg	4
BR-FL100W-07(ID:TA)	L385*W320*H140	5.8 kg	1	L405*W340*H310	12.95 kg	2
BR-FL120W-07(ID:TA)	L385*W320*H140	5.8 kg	1	L405*W340*H310	12.95 kg	2

Remarks:

1.White light series: WW (3000-3500K) NW (4000-4500K) CW (5000-6500K)

2.Luminous flux tolerance for ±10%

3.Products shall be subject to any changes without prior notices.



Through the 720H accelerated aging test,high and low temperature prediction in the rated under the working conditions after 35000H,will provide an average 70% optic maintenance ratio(L70).