


AIRCHILD

Features


- Operation From 3.0 to 40V Input
- Short Circuit Current Limiting
- Low Standby Current
- Output Switch Current of 1.5A Without External Transistors
- Output Voltage Adjustable
- Frequency Of Operation From 100Hz to 100KHz
- Step-Up, Step-Down or Inverting Switching Regulators

Description

The KA34063A is a monolithic regulator sub system intended for use as DC to DC converter. This device contains a temperature compensated bandgap reference, a duty cycle control oscillator, driver and high current output switch. It can be used for step down, step up or inverting switching regulators as well as for series pass regulators.



Internal Block Diagram



Absolute Maximum Ratings

Parameter	Symbol	Value	Unit	
Supply Voltage	V _{CC} 40		V	
Comparator Input Voltage Range	VI(COMP)	- 0.3 ~ + 40	V	
Switch Collector Voltage	VC(SW)	40	V	
Switch Emitter Voltage	VE(SW)	40	V	
Switch Collector To Emitter Voltage	VCE(SW)	40	V	
Driver Collector Voltage	VC(DR)	40	V	
Switch Current	ISW	1.5	A	
Storage Temperature Renge	TSTG	- 65 ~ + 150	°C	

Electrical Characteristics


(Vcc = 5.0V, TA = 0° C to +70°C , unless otherwise specified)


Parameter	Symbol	Conditions	Min.	Тур.	Max.	Unit	
OSCILLATOR				·			
Charging Current	ICHG	VCC = 5 to 40V TA = 25°C	22	31	42	μΑ	
Discharging Current	IDISCHG	$V_{CC} = 5 \text{ to } 40V$ $T_{A} = 25^{\circ}C$	140	190	260	μA	
Oscillator Amplitude	V(OSC)	TA = 25°C		0.5	-	V	
Discharge To Charge Current Ratio	к	V7 = VCC T _A = 25°C	5.2	6.1	7.5	-	
Current Limit Sense Voltage	VSENSE(C.L)	$I_{CHG} = I_{DISCHG}$ $T_A = 25^{\circ}C$	250	300	350	mV	
OUTPUT SWITCH							
Saturation Voltage 1 (Note)	VCE(SAT)1	I _{SW} = 1.0A V _C (driver) = V _C (SW)	-	0.95	1.3	V	
Saturation Voltage 2 (Note)	VCE(SAT)2	I _{SW} = 1.0A, V _C (driver) = 50mA	-	0.45	0.7	V	
DC Current Gain (Note)	GI(DC)	I _{SW} = 1.0A, V _{CE} = 5.0V, T _A = 25°C	50	180	-	-	
Collector off State Current (Note)	IC(OFF)	VCE = 40V, TA = 25°C	-	0.01	100	μΑ	
COMPARATOR							
Threshold Voltage	VTH	-	1.21	1.24	1.29	V	
Threshold Voltage Line Regulation	Δντη	VCC = 3 to 40V	-	2.0	5.0	mV	
Input Bias Current	IBIAS	$V_I = 0V$	-	50	400	nA	
TOTAL DEVICE							
Supply Current	ICC	V _{CC} = 5 to 40V CT = 0.001uF V7 = V _{CC} , V ₅ >V _{TH} pin2 = GND	-	2.7	4.0	mA	

Note :

Output switch tests are performed under pulsed conditions to minimize power dissipation








Mechanical Dimensions


Package



8-DIP

Mechanical Dimensions (Continued)

Package



8-SOP

Ordering Information

Product Number	Package	Operating Temperature	
KA34063A	8-DIP	0 ~ + 70°C	
KA34063AD	8-SOP	0~+70C	

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com